

TREADMILL MAINTENANCE BEGINNER COURSE


Level 1 • Detailed Training Workbook



TREADMILL MAINTENANCE BEGINNER COURSE


PRACTICAL MAINTENANCE
STEP-BY-STEP

1. SAFETY FIRST – POWER OFF & UNPLUG



- Turn off the treadmill and remove the safety key.
- Unplug the power cord from the wall outlet.
- Ensure the machine cannot be accidentally turned on.

2. CLEANING THE BELT AND DECK



- Remove dust, dirt and debris from the belt and deck.
- Use a mild, non-abrasive cleaner and a soft cloth.
- Do not use harsh chemicals or high-pressure cleaners.

3. LUBRICATING THE BELT



- Lift the belt and apply approved treadmill lubricant.
- Apply a thin, even layer (not too much).
- Reposition the belt and run the treadmill at low speed for a few minutes to spread the lubricant.

4. CHECKING BELT TRACKING



Rear Roller Adjustment

- Check the belt is centred and tracks smoothly.
- Use an Allen key to make small adjustments if needed.
- Do not over-tighten – make small changes and test.

5. INSPECTING THE ROLLERS AND DECK



- Check rollers for wear, noise or damage.
- Inspect the deck for cracks, warping or excessive wear.
- Ensure all bolts and fixings are tight.

6. CLEANING THE MOTOR COMPARTMENT



- Remove dust and debris from the motor area.
- Clean ventilation grills and fan (if fitted).
- Ensure good airflow and no blockages.

7. ELECTRICAL & SAFETY CHECKS



- Check power cord, plug and socket for damage.
- Inspect the safety key and emergency stop.
- Ensure console and buttons work correctly.

8. PREVENTIVE MAINTENANCE SCHEDULE

Task	Frequency
Clean belt and deck	Weekly
Check belt tracking	Weekly
Lubricate belt	Every 3-6 months (or 150-300 hrs)
Inspect rollers and deck	Every 3 months
Check motor compartment	Every 3 months
Electrical safety check	Monthly
Full service	Every 6-12 months

9. MAINTENANCE LOG SHEET

Date: _____		
Technician: _____		
Treadmill ID: _____		
Task	Done	Notes
Cleaned belt and deck	☐	
Checked belt tracking	☐	
Lubricated belt	☐	
Inspected rollers and deck	☐	
Checked motor compartment	☐	
Electrical/safety check	☐	
General condition	☐	

10. FINAL ASSESSMENT

- ☒ Perform full maintenance procedure
- ☒ Identify and fix common faults
- ☒ Complete maintenance log
- ☒ Demonstrate safe working practices
- ☒ Answer theory questions

W You're now equipped with the skills to maintain treadmills safely, reliably and run them at their best.

GYM SERVICE UK

TRAIN / MAINTAIN / KEEP ACTIVE

PROFESSIONAL | RELIABLE | NATIONWIDE

SAFETY • INSPECTION • PREVENTATIVE MAINTENANCE • FAULT RECOGNITION

Trainer-led / self-study edition • 2026

Welcome to the Course

This workbook is designed to give a beginner a structured understanding of treadmill maintenance. It deliberately separates routine observation and preventative care from specialist electrical or component-level work.

How to use this workbook

- Read the learning objectives before each module.
- Follow the safety notes before any practical activity.
- Use the checklists to record what you actually observed.
- Do not treat a generic procedure as a substitute for the treadmill manufacturer's manual.
- Ask a competent person when a task is outside your training or authorisation.

Core principle: a good maintenance technician does not simply adjust parts. They inspect, identify the likely cause, make the machine safe, carry out only work within their competence, test appropriately and document the result.

Course outcomes

- Identify common treadmill components and explain their purpose.
- Describe a safe pre-service and post-service inspection.
- Recognise belt, deck, roller, drive and incline conditions.
- Explain the difference between belt tracking and belt tension.
- Explain why lubrication requirements vary by treadmill.
- Use a structured troubleshooting process.
- Recognise faults requiring escalation or removal from service.
- Complete professional maintenance records and assessment paperwork.

Course Structure & Suggested Delivery

Module	Topic	Suggested time
1	Safety, isolation and risk awareness	30 min
2	Treadmill anatomy	25 min
3	Tools, PPE and work area	20 min
4	Inspection process	35 min
5	Running belt and deck	40 min
6	Lubrication	25 min
7	Tracking and tension	40 min
8	Cleaning and contamination	25 min
9	Rollers, drive and incline	35 min
10	Troubleshooting and fault recognition	40 min
11	Records and return to service	25 min
12	Knowledge + practical assessment	45–60 min

Suggested total: approximately 6–7 hours including practical observation and assessment. Actual duration should be adapted to learner experience and the treadmill models used.

Module 1 — Safety, Isolation & Risk Awareness

Learning objectives

- Explain why a treadmill should be made safe before maintenance.
- Describe the basic isolation sequence used in the workplace.
- Recognise conditions that require work to stop.
- Distinguish routine maintenance from specialist electrical work.

The safe sequence

1. Stop. Stop operation and allow movement to cease. **2. Isolate.** Follow the manufacturer's and workplace isolation procedure. **3. Secure.** Prevent accidental operation where required. **4. Inspect.** Establish the condition before touching or adjusting. **5. Work.** Perform only authorised tasks. **6. Reassemble.** Restore guards and covers. **7. Test.** Carry out appropriate checks before return to service.

Important: The exact isolation method varies by equipment and workplace. This workbook does not replace the manufacturer's service instructions or an employer's safe system of work.

Stop-work conditions

- Damaged mains cable, plug or exposed conductors.
- Smoke, burning smell, arcing or signs of electrical overheating.
- A damaged or defeated safety device.
- Serious frame, handrail or structural damage.
- A fault that cannot be safely identified within your competence.
- Repeated electrical protection trips or unexplained electrical behaviour.

Module 1 — Safety Exercise

Scenario 1

You arrive at a treadmill that a member reports as 'making a strange noise'. The machine is switched on, the belt is stationary and the console is illuminated.

Write the first five things you would do, in order:

1. _____
2. _____
3. _____
4. _____
5. _____

Scenario 2

You find a damaged power cable. The treadmill still appears to operate.

What is your response? _____

Who would you notify? _____

Trainer discussion

Ask the learner to explain why 'it still works' does not mean 'it is safe to use'.

Module 2 — Treadmill Anatomy

Main components

Component	Primary purpose	Beginner inspection
Console	User controls / information	Damage, display, buttons, cables where accessible
Safety key	Stops/interrupts operation according to design	Presence, condition, correct function
Running belt	Moving walking/running surface	Wear, damage, tracking, contamination
Running deck	Supports belt and influences friction	Wear, damage, lubrication system/type
Front/drive roller	Transfers/controls belt movement	Noise, damage, contamination
Rear roller	Supports and guides belt	Noise, damage, movement
Drive motor/system	Provides belt drive	Noise, heat signs, contamination, fault symptoms
Incline mechanism	Changes deck angle on equipped models	Smooth movement, abnormal noise, obstruction

Component identification exercise

On the treadmill used for training, point to each component above and explain its basic function to the assessor.

Learner notes: _____

Module 3 — Tools, PPE & Work Area

Typical beginner kit

- Manufacturer-approved cleaning materials.
- Manufacturer-approved lubricant where required.
- Suitable hand tools for permitted adjustments.
- Flashlight or inspection light.
- Clean lint-free cloths.
- Inspection/maintenance record.
- Workplace-required PPE.

Tool discipline

Use the correct tool for the fastener. Avoid damaged tools. Keep removed fasteners organised. Never leave tools on the running deck or inside the machine.

Work area

Keep the area clear of trip hazards. Control access where a treadmill is out of service. Keep cleaning products and loose items away from moving components.

Tool selection exercise

Task	Suitable approach	Learner notes
External cleaning	Approved cloth / cleaner	
Visual inspection	Light + checklist	
Permitted mechanical adjustment	Correct manufacturer-specified tool	
Electrical diagnosis	Specialist/competent procedure	

Module 4 — The 10-Minute Pre-Service Inspection

A repeatable inspection route

- Start at the console and work down the machine.
- Inspect frame and handrails before the moving system.
- Check the belt and deck visually.
- Inspect accessible rollers and drive areas.
- Look for contamination, loose hardware and signs of overheating.
- Record defects before making adjustments.
- Use the manufacturer's manual when a model-specific check is required.

Inspection point	Good	Monitor	Action	Notes
Frame / covers	■	■	■	
Handrails	■	■	■	
Power cable / plug	■	■	■	
Console / controls	■	■	■	
Safety key / function	■	■	■	
Belt	■	■	■	
Deck	■	■	■	
Rollers / drive area	■	■	■	
Incline	■	■	■	
Contamination / overheating	■	■	■	

Module 5 — Running Belt

What to inspect

- Top surface wear or glazing.
- Fraying or splitting at edges.
- Cracks, cuts or damaged sections.
- Discolouration or contamination.
- Uneven wear across the belt.
- Signs of belt drift or poor alignment.
- Excessive looseness or slipping during operation.

What the symptom can tell you

Symptom	Possible areas to investigate
Belt slips under load	Tension, belt condition, deck friction, drive system
Belt drifts to one side	Tracking, alignment, tension, wear
Jerky movement	Belt/deck condition, drive components, controller/motor system
Visible fraying	Belt condition, alignment, rubbing/contact, replacement need

Do not assume one symptom has one cause. Confirm the condition before adjusting.

Module 5 — Running Belt Practical

Learner task

With the treadmill safe and isolated, complete a visual belt inspection. Record five observations.

1. _____
2. _____
3. _____
4. _____
5. _____

Assessor prompts

- Where would you look for edge damage?
- What might uneven wear suggest?
- Why should you check the deck and belt together?
- When would you stop rather than adjust?

Module 6 — Running Deck & Friction

Why the deck matters

The running deck supports the belt and contributes to the friction characteristics of the moving surface. Wear, contamination or an incorrect lubrication condition can change how the treadmill behaves.

Inspection points

- Visible scoring, cracking or damage.
- Uneven wear.
- Contamination or residue.
- Manufacturer-specific lubrication/wax system.
- Evidence of excessive friction or heat symptoms.
- Any abnormal belt behaviour that may relate to the deck.

Beginner rule: do not sand, replace, lubricate or otherwise modify a deck unless the procedure is authorised and specified for that treadmill model.

Observation record

Condition	Observation	Action / escalation
Deck surface		
Belt underside (if accessible)		
Lubrication system/type		

Module 7 — Lubrication & Model-Specific Care

Why lubrication cannot be generic

Treadmills use different deck and belt systems. Some models specify silicone lubrication; others use different systems or may not require routine user-applied lubricant. The correct method, amount and frequency must come from the model-specific documentation.

Before applying anything

- Confirm make and model.
- Confirm the deck/belt system.
- Check the manufacturer's maintenance procedure.
- Use only the specified product.
- Follow the specified application method and quantity.
- Record the maintenance action.

Never improvise. General-purpose oils or household lubricants are not a substitute for a specified treadmill product.

Lubrication record

Date	Model	Product specified	Procedure followed	Result	Initials

Module 8 — Belt Tracking

Understanding tracking

Tracking is the belt's position between the side rails. A belt that repeatedly moves off-centre should be investigated rather than repeatedly corrected without understanding the cause.

Beginner adjustment principles

- Use the manufacturer's adjustment points.
- Make small, controlled changes.
- Keep both sides of the adjustment system understood.
- Re-check alignment after each change.
- Do not use excessive force.
- Stop if the procedure is unclear or the belt condition is suspect.

Model-specific adjustment direction and amount are not universal. Use the service manual.

Tracking observation

Before adjustment: _____ After adjustment: _____

Module 9 — Belt Tension

Too loose

Possible symptoms include slipping, poor power transfer, hesitation or belt movement under load.

Too tight

Possible consequences include increased friction, additional mechanical loading and premature wear.

Correct approach

Use the manufacturer's specification or procedure. Consider belt condition, deck condition, tracking and drive components before tightening.

Question	Learner answer
What symptom suggests slipping?	
What can excessive tension cause?	
Why should you inspect before adjusting?	
Where do you find the model-specific procedure?	

Module 10 — Cleaning & Contamination

External cleaning

- Isolate where required by the cleaning procedure.
- Use the approved product.
- Apply cleaner in the controlled way specified by the manufacturer.
- Keep liquid away from electronics.
- Clean handrails, console, frame and footrails.
- Remove residue rather than leaving a slippery surface.

Internal contamination

Dust and debris can affect cooling and mechanical components. Internal cleaning must follow the manufacturer's procedure and workplace controls.

Cleaning inspection

Area	Before	After	Notes
Console			
Handrails			
Frame / covers			
Footrails			
Accessible drive area			

Module 11 — Rollers & Drive System

Roller checks

Look for abnormal noise, roughness, visible damage, contamination or unusual movement. Do not place hands near moving components during operation.

Drive-system clues

- Grinding or rumbling noise.
- Belt slipping under load.
- Burning smell or overheating signs.
- Unusual vibration.
- Repeated fault messages or shutdowns.

These symptoms can have multiple causes. Use a structured inspection rather than changing several variables at once.

Module 12 — Incline System

For beginner training, focus on safe observation: commanded movement, smoothness, unusual noise, visible obstruction/damage and whether the system behaves as expected.

Exposed electrical diagnosis, controller testing and component replacement should be undertaken only by appropriately trained and authorised personnel.

Module 13 — Structured Troubleshooting

The 6-step method

1. Define the symptom clearly.
2. Make the machine safe.
3. Gather evidence: model, fault message, noise, behaviour and recent maintenance.
4. Inspect the simplest relevant causes first.
5. Change one variable at a time and follow the manual.
6. Test, document and escalate if unresolved.

Fault-finding worksheet

Symptom	Evidence observed	Possible cause	Action	Result

Module 14 — Fault Recognition & Escalation

Condition	Beginner response
Damaged mains cable / exposed conductor	Stop use and escalate
Smoke / burning smell / arcing	Stop, isolate safely and escalate
Defeated or damaged safety function	Do not return to service
Severe structural damage	Stop use and escalate
Unknown electrical fault	Do not improvise; escalate
Minor cosmetic damage	Record and assess according to workplace process
Normal cleaning requirement	Complete using approved procedure

Escalation record

Fault: _____

Immediate action: _____

Person / team notified: _____

Equipment status: ☐ Available ☐ Monitor ☐ Out of service

Module 15 — Return to Service

Final verification

- All tools and loose materials removed.
- Covers and guards correctly refitted.
- Belt condition acceptable.
- Tracking checked.
- Tension checked according to procedure.
- Safety functions checked.
- Cleaning complete.
- No unresolved stop-work condition remains.
- Maintenance record completed.
- Relevant staff informed of any remaining issue.

Return-to-service declaration

I confirm that I have completed the checks within my competence and recorded any outstanding issue.

Learner: _____ Date: _____ Assessor: _____

Module 16 — Professional Maintenance Records

A maintenance record should allow another person to understand what was inspected, what was found and what happened next.

Date	Asset / Model	Hours / use	Finding	Action	Status	Initials

Module 17 — Learner Exercises

Exercise 1 — Explain the difference

In your own words, explain the difference between belt tracking and belt tension.

Exercise 2 — Choose the next action

Situation	Your action
Belt is slightly off-centre after cleaning	_____
Mains cable is damaged	_____
Manual says no routine lubrication is required	_____
New grinding noise appears	_____
Console needs cleaning	_____

Exercise 3 — Explain your reasoning

Why is it important to diagnose before adjusting? _____

Module 18 — Knowledge Assessment

1. What is the first priority before maintenance?
A Speed test B Safe isolation C Lubrication D Belt adjustment
2. Why is the manufacturer's manual important?
A It gives model-specific procedures B It is optional C It replaces safety D It only covers cleaning
3. Belt tracking means:
A Alignment B Lubricant type C Speed D Deck thickness
4. Excessive belt tension may increase:
A Friction and loading B Safety C Cooling D Display brightness
5. What should you do with a damaged mains cable?
A Ignore it B Tape it and use C Stop use and escalate D Lubricate it
6. Should every treadmill receive the same lubricant?
A Yes B No C Only older models D Only commercial models
7. A new grinding noise should be:
A Masked B Investigated safely C Ignored D Tightened away
8. Why record maintenance?
A Traceability and communication B Decoration C To replace manuals D To increase speed
9. If a fault is beyond your competence:
A Guess B Bypass C Escalate D Continue
10. Before return to service you should:
A Leave guards off B Verify relevant safety and maintenance checks C Remove the safety key D Skip records
11. What should you do before a permitted adjustment?
A Confirm the correct procedure B Make a large change C Guess direction D Change both sides randomly
12. What can contamination affect?
A Mechanical/electrical operation B Nothing C Certificate validity D Belt colour

Score: _____ / 12 Recommended pass standard: 80%+

Knowledge Answer Sheet

1 B

2 A

3 A

4 A

5 C

6 B

7 B

8 A

9 C

10 B

11 A

12 A

Learner result

Score: _____ / 12 Percentage: _____% ■ Pass ■ Further study

Trainer comments: _____

Practical Assessment — Part 1

Learner: _____ Date: _____ Asset / Model: _____

Safety & preparation

- Competent ■ Revisit Explains safe isolation.
- Competent ■ Revisit Identifies stop-work conditions.
- Competent ■ Revisit Uses appropriate PPE/work-area controls.
- Competent ■ Revisit Keeps tools and materials controlled.
- Competent ■ Revisit Explains the limits of their competence.

Inspection

- Competent ■ Revisit Frame/covers
- Competent ■ Revisit Handrails
- Competent ■ Revisit Power cable/plug
- Competent ■ Revisit Console
- Competent ■ Revisit Safety key
- Competent ■ Revisit Belt
- Competent ■ Revisit Deck
- Competent ■ Revisit Rollers
- Competent ■ Revisit Drive area
- Competent ■ Revisit Incline

Assessor observations

Practical Assessment — Part 2

Maintenance understanding

- Competent ■ Revisit Explains belt wear indicators.
- Competent ■ Revisit Explains tracking.
- Competent ■ Revisit Explains tension.
- Competent ■ Revisit Checks lubrication requirement against documentation.
- Competent ■ Revisit Uses appropriate cleaning method.
- Competent ■ Revisit Recognises fault escalation points.
- Competent ■ Revisit Completes a maintenance record.
- Competent ■ Revisit Completes return-to-service checks.

Practical result

- Competent ■ Further practice required

Assessor: _____ Signature: _____

Learner: _____ Signature: _____

Detailed Preventative Maintenance Checklist

Area	Check	Status	Notes
Safety	Safety key/function	■ OK ■ Action	
Electrical	Cable/plug/visible damage	■ OK ■ Action	
Structure	Frame/handrails/covers	■ OK ■ Action	
Controls	Console/buttons/display	■ OK ■ Action	
Belt	Wear/edges/condition	■ OK ■ Action	
Belt	Tracking	■ OK ■ Action	
Belt	Tension per procedure	■ OK ■ Action	
Deck	Condition/friction/lubrication system	■ OK ■ Action	
Rollers	Noise/condition	■ OK ■ Action	
Drive	Noise/contamination	■ OK ■ Action	
Incline	Movement/obstruction/noise	■ OK ■ Action	
Cleaning	External surfaces	■ OK ■ Action	
Final	Return-to-service checks	■ OK ■ Action	

Trainer Guide & Marking Notes

What good performance looks like

- Learner makes the equipment safe before maintenance.
- Learner observes before adjusting.
- Learner uses model-specific information rather than guessing.
- Learner can explain belt/deck/roller relationships.
- Learner recognises electrical and serious mechanical escalation points.
- Learner documents work clearly.

Suggested practical marking

Safety is a critical element. A learner who bypasses a safety device, continues with a serious electrical hazard or knowingly works beyond competence should not be signed off for that task.

Feedback

GYM SERVICE UK

CERTIFICATE OF COMPLETION

TREADMILL MAINTENANCE — BEGINNER

This certifies that

has completed Level 1 Beginner Treadmill Maintenance Training.

Learner / Technician	_____
Date	_____
Certificate No.	_____
Trainer / Assessor	_____

Educational course completion only. This certificate does not by itself certify electrical competence or authorise work outside the learner's competence.